

1 BT-250 Remote



Power	TV Power Button
Green	STB - Standby, Power ON/OFF
Red	Source
Yellow	Source Volume + / Volume -
Blue	Favourite Channels
Star	Search
Search	Search
Server	Server Settings
Category	To view categories when in Live TV/EPG/TV Series/VOD Menus
Live TV	Live TV
VOD	Video On Demand
TV Series	TV Series
PVR	Personal Video Recorder
Menu	Menu
Guide	Guide
Arrows	Arrow Keys / OK
Back	Back
Home	Home
Pointer	Pointer
VOL	Volume - Up (+) / Down (-)
Info	Information
Last Channel	Last Channel
CH	Channel - Up (+) / Down (-)
Rewind	Rewind
Play/Pause	Play/Pause
Fast Forward	Fast Forward
Record	Record
Stop	Stop
Mute	Mute
Red Button	Red Button
Green Button	Green Button
Yellow Button	Yellow Button
Blue Button	Blue Button
Number Pad	Number Pad
PG Down	Page Down
PG Up	Page Up

2 BT-250 Remote - Learning Function

The learning function on the IR-200 remote is used to control your TV. You will be able to control: Power ON/OFF, Volume and Input Source. To do this you will need the factory remote control for your TV.



1. On the BT-250, press and hold the TV POWER + TV SOURCE for 3 seconds. Once the red light turns on, release the buttons.

2. Press the learning key you would like to program (TV POWER/SOURCE/ TV VOL+/ TV VOL-) and the red light will start flashing. The flashing red light indicates the BT-250 is in learning mode.



3. Align your TV Remote and the BT-250 so that the front transmitters are pointing at each other. They should be within 1 inch or 3 cm of each other.

4. Press the button that you want to learn on the original remote. After receiving a learning function successfully, the red light on the BT-250 will blink 4 times.

5. To learn other keys, repeat Steps 2-4

6. After entering the learning mode, you can exit the learning mode by short pressing the "TV POWER + TV SOURCE" keys.



3 BT-250 Remote - Bluetooth Pairing

1. On your BuzzTV device, navigate to Settings > Remotes & Accessories > toggle Bluetooth to ON. Then choose: Add Accessory.

2. On the BT-250, press and hold the VOL - & the OK Button for 3 seconds. Once the red light starts flashing, release the buttons.



3. Select "BuzzTV BT-250" on your BuzzTV Device.

4. You are now Bluetooth Paired. You can confirm this by looking for "BuzzTV BT-250" under the Remotes and Accessories Menu.

Note:

If you do not select the key within 15 seconds after entering the learning state, it will automatically exit the learning state.

Please note not all TVs are compatible with source pairing

CEC settings to support the BT-250, your TV & your BuzzTV Box

If you were successful in TV source pairing the BT-250 to your TV then you need to make sure the CEC settings on both the TV and your BuzzTV Box are enabled and in some cases in the correct HDMI port on the TV, refer to your TV manual if needed. (Initially set to ON)